

## DC6430 Dual Directional Coupler

- 15,000 Watts
- 80–1000MHz

### Features

The Model DC6430 is a dual directional coupler with excellent frequency range and power handling capability. The wide range assures flexibility in coupling high power amplifiers to oscilloscopes, voltmeters, power meters, spectrum analyzers and other measuring instruments. The dual directional design allows the user to monitor both forward and reflected power, a much needed characteristic in RF susceptibility testing for amplifier overdrive protection, field control and load protection. Low insertion loss allows efficient coupling to the load.

The Model DC6430 is uniquely suited for use with our 6000W1000 power amplifier, and other amplifiers operating within this frequency and power range.

The export classification for this equipment is EAR99. These commodities, technology or software are controlled for export in accordance with the U.S. Export Administration Regulations. Diversion contrary to U.S. law is prohibited.

### Specifications

**FREQUENCY RANGE:** 80 MHz–1000 MHz

**POWER (Maximum):** 15 kW CW

**COUPLING FACTOR:** 68 dB

**COUPLING FLATNESS:**  $\pm 1.0$  dB

**DIRECTIVITY:** Typical, 20 dB; Minimum, 18 dB

**INSERTION LOSS:** 0.1 dB maximum

**IMPEDANCE (Main Line):** 50 ohms, VSWR 1.15:1 maximum

**CONNECTORS:**

Main Line, Type EIA fixed/swivel flanges, 3-1/8"  
Coupled, Type N female

**WEIGHT (Maximum):** 3.0 kg (6.6 lbs)

**SIZE (WxH):** 15.2 x 13.2 cm (6.0 x 5.2 in)

**EXPORT CLASSIFICATION:** EAR99

AR RF/Microwave  
Instrumentation  
160 School House Rd  
Souderton, PA 18964  
215-723-8181

For an applications engineer call: 800.933.8181

[www.arworld.us](http://www.arworld.us)

To order AR Products, call 215.723.8181. For an applications engineer call: 800.933.8181. Direct to Service call: 215.723.0275 or email: [service@arworld.us](mailto:service@arworld.us) For Faxing Orders: 866.859.0582 (Orders Only Please) [info@arworld.us](mailto:info@arworld.us)  
Approved for public release by AR RF/Microwave Instrumentation

020117

